	Title:	Performance report for SiT3373, 320 MHz, LVDS		
	Type:	Performance report	Rev:	1.2
	Orig:		Date:	September 12, 2018

Performance report for SiT3373 - 320 MHz, LVDS

This performance report contains the following data:

- Phase noise
- Random phase jitter
- Output waveforms
- Pull range linearity
- Frequency stability over temperature
- Period jitter
- Duty cycle
- Rise/Fall time
- Amplitude
- Current consumption



Title:	Performance report for SiT3373, 320 MHz, LVDS		
Type:	Performance report	Rev:	1.2
Orig:		Date:	September 12, 2018




Figure 1: Phase noise, 3.3 V

**Integrated phase jitter value applies for ±50 ppm to ±400 ppm pull ranges*

Table 1: Phase noise

Phase noise dBc/Hz					
Frequency offset (Hz)	Pull range (ppm)				
	±50	±100	±150	±200	±400
1	-38.2	-30.9	-28.7	-24.4	-19.1
10	-63.5	-61.2	-59.4	-56.1	-51.1
100	-90.2	-85.8	-82.6	-79.9	-73.7
1 K	-110.9	-105.8	-102.5	-99.7	-94.2
10 K	-124.4	-123.4	-122.3	-121.0	-116.7
100 K	-126.6	-126.5	-126.5	-126.2	-126.5
1 M	-143.0	-143.0	-143.0	-142.9	-142.9
10 M	-153.5	-153.6	-153.4	-153.5	-153.0
40 M	-155.9	-155.8	-155.9	-155.8	-155.1



	Title:	Performance report for SiT3373, 320 MHz, LVDS		
	Type:	Performance report	Rev:	1.2
	Orig:		Date:	September 12, 2018

Table 2: Integrated Phase jitter

Parameter	Units	Pull range (ppm)
		±50 to ±400
Integrated Phase jitter (1.875 MHz - 20 MHz)	fs, rms	70
Integrated Phase jitter (12 kHz - 20 MHz)	fs, rms	204

The information contained in this document is confidential and proprietary to SiTime Corporation. Unauthorized reproduction or distribution is prohibited.

	Title:	Performance report for SiT3373, 320 MHz, LVDS		
	Type:	Performance report	Rev:	1.2
	Orig:		Date:	September 12, 2018




Figure 2: Output waveform, 2.5 V




Figure 3: Output waveform, 3.3 V

The information contained in this document is confidential and proprietary to SiTime Corporation. Unauthorized reproduction or distribution is prohibited.



Title:	Performance report for SiT3373, 320 MHz, LVDS		
Type:	Performance report	Rev:	1.2
Orig:		Date:	September 12, 2018




Figure 4: Frequency pull characteristic

SiTime	Title:	Performance report for SiT3373, 320 MHz, LVDS		
	Type:	Performance report	Rev:	1.2
	Orig:		Date:	September 12, 2018




Figure 5: Frequency stability* over temperature, 2.5 V – 3.3 V, 30 devices

*SiT3373 frequency stability is independent of output frequency.

The information contained in this document is confidential and proprietary to SiTime Corporation. Unauthorized reproduction or distribution is prohibited.



	Title:	Performance report for SiT3373, 320 MHz, LVDS		
	Type:	Performance report	Rev:	1.2
	Orig:		Date:	September 12, 2018

Table 3: Summary performance data

Parameter	Units	Voltage	
		2.5 V	3.3 V
Period jitter	ps, rms	0.73	0.67
Period jitter (simple size 10,000 cycles)	ps, pk-pk	5.33	5.38
Duty cycle	%	49.9	49.9
Rise time (20% - 80%)	ps	376	381
Fall time (80% - 20%)	ps	370	375
Differential voltage swing	V	0.80	0.81
Current consumption (no load, output enabled)	mA	75.7	75.9
Current consumption (no load, output disabled)	mA	57.1	57.1

	Title:	Performance report for SiT3373, 320 MHz, LVDS		
	Type:	Performance report	Rev:	1.2
	Orig:		Date:	September 12, 2018


Test description

Conditions:

- Frequency: 320 MHz
- VDD: 2.5 V, 3.3 V
- Pull range: ± 50 ppm, ± 100 ppm, ± 150 ppm, ± 200 ppm, ± 400 ppm
- Temperature: 25 °C

Equipment:

Model	Measurement / Purpose
Keysight DSA90604A (6 GHz, 20 Gbps)	Period jitter, output amplitude, rise/fall time, duty cycle
Keysight 5052B Signal Source Analyzer	Phase noise, integrated phase jitter
Keysight 34980A	Power supply current
Keysight E3631A	Power supply
Keysight 53230A	Frequency

	Title:	Performance report for SiT3373, 320 MHz, LVDS		
	Type:	Performance report	Rev:	1.2
	Orig:		Date:	September 12, 2018

Setup

Waveform

For waveform parameters measurement (rise/fall time, differential swing, duty cycle), both DUT outputs are terminated with 100 Ω differential. Output signals are measured using Keysight 1134B active probe with Keysight N5425B probe head. All measurements are applied to the differential waveform. Figure 6 shows test setup diagram for waveform parameters measurement.




Figure 6. Test setup for measuring waveform parameters (rise/fall time, differential swing, duty cycle)

Period Jitter

For period jitter measurement outputs are connected through AC-coupling capacitors to the oscilloscope channels. Signals are subtracted inside the oscilloscope. All measurements applied to differential waveform. Figure 7 shows test setup diagram for period jitter measurement.




Figure 7. Test setup for measuring period jitter

SiTime	Title:	Performance report for SiT3373, 320 MHz, LVDS		
	Type:	Performance report	Rev:	1.2
	Orig:		Date:	September 12, 2018

Phase noise

For phase noise measurements, differential signal is converted to single-ended using impedance matching transformer. Transformer's output is connected to measurement instrument. Figure 8 shows test setup diagram for phase noise measurement.




Figure 8. Test setup for measuring phase noise.

Current consumption

For Current consumption measurement device output is floating. For frequency measurement differential-to-single-ended converter is used.