

Title:	Performance Report SiT1602B, 26MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	

This report contains sample performance data for SiT1602B-26MHz.

Conditions:

- Frequency 26 MHz
- Vdd 1.8V, 2.5V, 2.8V, 3.0V, 3.3V
- Temperature 25°C
- Termination:
 - No load for IDD
 - \circ 50 Ω to GND for phase noise
 - o 15pF for other tests

Equipment:

- Agilent DSA90604 oscilloscope (6GHz, 20Gsps)
 - o Period jitter, waveform, rise/fall time, duty cycle, amplitude
- Agilent E5052B Signal Source Analyzer
 - o Phase noise, integrated phase jitter
- Power supply current
 - o Agilent 34401A DMM

Data:

- Random Phase jitter, Period Jitter, Duty cycle, Rise/Fall time, Amplitude, Idd
- Output waveforms
- Frequency stability versus temperature

Table 1. Performance data

Parameter	Units	Voltage				
raiametei	Office	1.8 V	2.5 V	2.8 V	3.0 V	3.3 V
Random Phase jitter (900kHz - 5MHz)	ps, rms	0.51	0.54	0.53	0.53	0.53
Random Phase jitter (12kHz - 5MHz)	ps, rms	1.32	1.30	1.30	1.30	1.30
Random Phase jitter (900kHz - 20MHz)*	ps, rms	0.78	0.82	0.82	0.81	0.81
Random Phase jitter (12kHz - 20MHz)*	ps, rms	1.44	1.44	1.44	1.44	1.44
Period jitter	ps, rms	1.80	1.59	1.55	1.53	1.54
Period jitter (10,000 cycles)	ps, pk-pk	13.8	12.3	12.0	12.0	11.6
Duty cycle	%	50.0	49.9	50.1	50.2	50.4
Rise time (20% - 80%)	ns	1.25	1.02	0.94	0.99	0.93
Fall time (80% - 20%)	ns	1.26	0.98	0.91	0.96	0.93
Amplitude	V	1.78	2.48	2.77	3.00	3.30
Current consumption (no load, output enabled)	mA	3.63	3.78	3.83	3.87	3.94
Current consumption (no load, output disabled)	mA	3.41	3.48	3.53	3.58	3.65

^{*}Calculated by extending the noise floor of the phase noise from 5 MHz to 20 MHz



Title:	Performance Report SiT1602B, 26MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	



Figure 1. Duty cycle, Rise/Fall time and Amplitude 1.8V



Title:	Performance Report SiT1602B, 26MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 2. Duty cycle, Rise/Fall time and Amplitude 2.5V



Title:	Performance Report SiT1602B, 26MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 3. Duty cycle, Rise/Fall time and Amplitude 2.8V



Title:	Performance Report SiT1602B, 26MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	



Figure 4. Duty cycle, Rise/Fall time and Amplitude 3.0V



Title:	Performance Report SiT1602B, 26MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 5. Duty cycle, Rise/Fall time and Amplitude 3.3V



Title:	Performance Report SiT1602B, 26MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 6. Frequency stability* versus temperature, 1.8 V

^{*}Please note that frequency stability in SiTime devices is not depended on output frequency.



Title:	Performance Report SiT1602B, 26MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 7. Frequency stability versus temperature, 2.5 V



Title:	Performance Report SiT1602B, 26MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 8. Frequency stability versus temperature, 2.8 V



Title:	Performance Report SiT1602B, 26MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 9. Frequency stability versus temperature, 3.0 V



Title:	Performance Report SiT1602B, 26MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 10. Frequency stability versus temperature, 3.3 V