

Title:	Performance Report SiT1602B, 50MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	

## This report contains sample performance data for SiT1602B-50MHz.

## Conditions:

- Frequency 50 MHz
- Vdd 1.8V, 2.5V, 2.8V, 3.0V, 3.3V
- Temperature 25°C
- Termination:
  - No load for IDD
  - $\circ$  50 $\Omega$  to GND for phase noise
  - o 15pF for other tests

## **Equipment:**

- Agilent DSA90604 oscilloscope (6GHz, 20Gsps)
  - o Period jitter, waveform, rise/fall time, duty cycle, amplitude
- Agilent E5052B Signal Source Analyzer
  - o Phase noise, integrated phase jitter
- Power supply current
  - o Agilent 34401A DMM

## Data:

- Random Phase jitter, Period Jitter, Duty cycle, Rise/Fall time, Amplitude, Idd
- Output waveforms
- Frequency stability versus temperature

Table 1. Performance data

Parameter	Units	Voltage				
i didilictei	Offics	1.8 V	2.5 V	2.8 V	3.0 V	3.3 V
Random Phase jitter (900kHz - 20MHz)	ps, rms	0.60	0.64	0.65	0.67	0.67
Random Phase jitter (12kHz - 20MHz)	ps, rms	1.28	1.31	1.32	1.34	1.34
Period jitter	ps, rms	1.59	1.42	1.34	1.33	1.32
Period jitter (10,000 cycles)	ps, pk-pk	12.2	11.3	10.9	11.0	10.5
Duty cycle	%	49.9	49.8	50.2	50.5	50.8
Rise time (20% - 80%)	ns	1.25	1.00	0.91	0.96	0.94
Fall time (80% - 20%)	ns	1.26	0.97	0.89	0.95	0.91
Amplitude	V	1.77	2.45	2.73	2.95	3.27
Current consumption (no load, output enabled)	mA	3.95	4.17	4.28	4.33	4.45
Current consumption (no load, output disabled)	mA	3.46	3.53	3.58	3.62	3.70



Title:	Performance Report SiT1602B, 50MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	



Figure 1. Duty cycle, Rise/Fall time and Amplitude 1.8V



Title:	Performance Report SiT1602B, 50MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 2. Duty cycle, Rise/Fall time and Amplitude 2.5V



Title:	Performance Report SiT1602B, 50MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	



Figure 3. Duty cycle, Rise/Fall time and Amplitude 2.8V



Title:	Performance Report SiT1602B, 50MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	



Figure 4. Duty cycle, Rise/Fall time and Amplitude 3.0V



Title:	Performance Report SiT1602B, 50MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 5. Duty cycle, Rise/Fall time and Amplitude 3.3V



Title:	Performance Report SiT1602B, 50MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 6. Frequency stability\* versus temperature, 1.8 V

<sup>\*</sup>Please note that frequency stability in SiTime devices is not depended on output frequency.



Title:	Performance Report SiT1602B, 50MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 7. Frequency stability versus temperature, 2.5 V



Title:	Performance Report SiT1602B, 50MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 8. Frequency stability versus temperature, 2.8 V



Title:	Performance Report SiT1602B, 50MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 9. Frequency stability versus temperature, 3.0 V



Title:	Performance Report SiT1602B, 50MHz			
Type:	Performance report	Rev:	1.0	
Orig:		Date:	Mar 31, 2014	




Figure 10. Frequency stability versus temperature, 3.3 V